



Cembre



15 | 137 E

COPPER LUGS LONG BARREL 2A-M SERIES



GENERAL INFORMATIONS

- UL listed per 486 A up to 35 kV (File nr. E125401).
- The lugs are for use with Cu wire.
- The lugs are manufactured from electrolytic copper tube, annealed to guarantee optimum ductility and electrolytically tin plated to avoid oxidation.
- The tongue is clearly marked with wire size and stud hole dimension.

INSTALLATION INSTRUCTIONS

- 1) Select proper lug for the Cu wire size used.
- 2) Strip the cable insulation for a length equal to that of the terminal barrel.
- 3) Insert conductor into the barrel.
- 4) Select the proper die as indicated in the table.
- 5) Apply the proper # of crimps, as indicated in the same table.

 **Cembre** _____ www.cembre.com

Cembre S.p.A.
Via Serenissima, 9
25135 Brescia (Italia)
Telefono: 030 36921
Telefax: 030 3365766
E-mail: sales@cembre.com
www.cembre.com

Cembre Ltd.
Dunton Park
Kingsbury Road, Curdworth - Sutton Coldfield
West Midlands B76 9EB (UK)
Tel.: 01675 470440 - Fax: 01675 470220
E-mail: sales@cembre.co.uk
www.cembre.co.uk

Cembre S.a.r.l.
22 Avenue Ferdinand de Lesseps
91420 Morangis (France)
Tél.: 01 60 49 11 90 - Fax: 01 60 49 29 10
CS 92014 - 91423 Morangis Cédex
E-mail: info@cembre.fr
www.cembre.fr

Cembre España S.L.U.
Calle Verano 6 y 8
28850 Torrejón de Ardoz
Madrid (España)
Teléfono: 91 4852580 - Fax: 91 4852581
E-mail: comercial@cembre.es
www.cembre.es

Cembre GmbH
Heidemannstraße 166
80939 München (Deutschland)
Telefon: 089 3580676
Telefax: 089 3580677
E-mail: sales@cembre.de
www.cembre.de

IKUMA GmbH & Co. KG
Boschstraße 7
71384 Weinstadt (Deutschland)
Telefon: 7151 20536-60
Telefax: 7151 20536-80
E-mail: info@ikuma.de
www.ikuma.de

Cembre Inc.
Raritan Center Business Park
181 Fieldcrest Avenue
Edison, New Jersey 08837 (USA)
Tel.: (732) 225-7415 - Fax: (732) 225-7414
E-mail: sales.US@cembreinc.com
www.cembreinc.com



SIZES	CONDUCTOR RANGE			INSTALLATION TOOLING (# of crimps)					
				50 kN		120 - 130 kN		230 kN	520 kN
				6 sh tons		13.5 - 14.6 sh tons		25.8 sh tons	58.4 sh tons
LUGS	[AWG] [MCM]	low str	fine str	HT51 with suffix L, L-KV; RH50, RHM50, B51 with suffix L, A, LA, KV, LA-KV; B500 with suffix A, KV, A-KV	HT120, HT120-KV; HT131 with suffix -C, U-C, LN-C; RHC131 with suffix LN, -KV; RHM132; RHU131-C; B135, B1350, B131, B1300 with suffix C, -CA, LN-C, LN-CA, C-KV, CA-KV, L-C-KV, LN-CA-KV, -UC	ECW-H3D	RHU520		
		[mm ²]						DIE SET	NEST + INTENDOR
		2A3	6 AWG	16		ME3-50 (2)	MA3+PA10-C (2)	ME3-C (2)	AU230-130D ADAPTER + 130 kN dies
2A5	4 AWG	25		ME5-50 (2)	MA5+PA10-C (2)	ME5-C (2)			
2A7	2 AWG	35	25-35	ME7-50 (2)	MA7+PA10-C (2)	ME7-C (2)			
2A10	2-1/0 AWG	50	35-50	ME10-50 (3)	MA10+PA10-C (2)	ME10-C (2)			
2A14	1/0-2/0 AWG	70	50-70	ME14-50 (3)	MA14+PA24-C (2)	ME14-C (2)			
2A19	2/0-3/0 AWG	95	70-95	ME19-50 (3)	MA19+PA24-C (2)	ME19-C (2)			
2A24	3/0-250 AWG	120	95-120	ME24-50 (4)	MA24+PA24-C (3)	ME24-C (3)			
2A30	250-300 MCM	150	120-150	ME30-50 (5)	MA30+PA48-C (3)	ME30-C (3)			
2A37	300-350 MCM	185	150-185	ME37-50 (5)	MA37+PA48-C (3)	ME37-C (3)			
2A48	350-500 MCM	240	185-240	ME48-50 (5)	MA48+PA48-C (3)	ME48-C (3)			
2A60	500-600 MCM	300	240-300	-	MA60+PA60-C (1)	ME60-C (5)			
2A80	800 MCM	400	300-400	-	-	ME80-C (6)	ME80-3D (3)	ME80-520 (3)	